

# Vali2+ 6bz7a 300R 0dBu STD TESTS UNBAL REPORT

Overall Result: PASS

SUMMARY:	RESULT
A01 Ampl, Phase, Gain	✓
A02 Ampl, Phase vs Freq	✓
A03 Gain vs Ampl	✓
A04 THD+N, THD, nth-HD 2 3 4 - THD+N minus 2nd and 3rd harmonics	✓
A05 THD+N vs Freq	✓
A06 THD+N vs Ampl	✓
A07 Noise, SNR	✓
A08 Crosstalk A to B	✓
A09 Crosstalk B to A	✓
A10 Crosstalk A to B vs Freq	✓
A11 Crosstalk B to A vs Freq	✓
A12 FFT 1000 Hz THD+N	✓
A13 FFT 50+7000Hz	✓
A14 FFT 600+1700 Hz	✓
A15 FFT 19+20 KHz	✓
A16 FFT residual noise	✓

KEY: ✓ = Test passes, ✗ = Test fails, OK = Test has run but has no limit checking, (✗) = Test has failed to run or has not completed, [✓] = Test passes but is not required, [✗] = Test fails but is not required, ? = Test is required but has not been run.  
- = Test is not required.

[Back to top](#)

## A01 Ampl, Phase, Gain: PASSED

Measured at 11/20/2020 12:08:44 PM

Generator Settings	
Channel A:	sine, 0 dBu at 1000 Hz
Channel B:	sine, 0 dBu at 1000 Hz

Signal Analyzer Readings		
RMS amplitude (Channel A)	0.061 dBu	< 3 dBu > -3 dBu
RMS amplitude (Channel B)	-0.075 dBu	< 3 dBu > -3 dBu
Inter-channel phase	-0.05 °	< 10 ° > -10 °

CTA Readings		
Gain (Channel A RMS)	0.061 dB	< 3 dB > -3 dB
Gain (Channel B RMS)	-0.075 dB	< 3 dB > -3 dB
Settings: Generator relative, 22 Hz - 22 kHz, unweighted RMS with 1/3rd octave band-pass filter at the generator frequency		


[Back to top](#)

## A02 Ampl, Phase vs Freq: PASSED


Measured at 11/20/2020 12:08:47 PM

Generator Settings	
Channel A:	sine, -3 dBFS at 1000 Hz
Channel B:	sine, -3 dBFS at 1000 Hz

# Frequency Response and Inter-channel Phase



# Frequency Response and Inter-channel Phase




[Back to top](#)

A03 Gain vs Ampl: PASSED

Measured at 11/20/2020 12:08:53 PM


Generator Settings	
Channel A:	sine, 0 dBu at 1000 Hz
Channel B:	sine, 0 dBu at 1000 Hz

Gain vs Amplitude



Line	Name	Points	Log X	Log Y	Cursor X	Cursor Y	Comment/Label
1	Sweep of CT Det.: Gain: Ch A	25	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	
2	Max limit Sweep of CT Det.: Gain: Ch A	3	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	1: Sweep timed out
3	Min limit Sweep of CT Det.: Gain: Ch A	3	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	

Gain vs Amplitude



Line	Name	Points	Log X	Log Y	Cursor X	Cursor Y
1	Sweep of CT Det.: Gain: Ch B	25	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
2	Max limit Sweep of CT Det.: Gain: Ch B	3	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
3	Min limit Sweep of CT Det.: Gain: Ch B	3	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

[Back to top](#)

A04 THD+N, THD, nth-HD 2 3 4 - THD+N minus 2nd and 3rd harmonics: **PASSED**

Measured at 11/20/2020 12:09:05 PM

#### Generator Settings

Channel A:	sine, 0 dBu at 1000 Hz
Channel B:	sine, 0 dBu at 1000 Hz

#### Signal Analyzer Readings

RMS amplitude (Channel A)	0.062 dBu	Not limit checked.
RMS amplitude (Channel B)	-0.072 dBu	Not limit checked.

#### CTA Readings

THD+N - relative (Channel A RMS)	0.21802 %	< 200 % > 0 %
THD+N - relative (Channel B RMS)	0.21259 %	< 200 % > 0 %

Settings: Self relative, 22 Hz - 22 kHz, unweighted RMS with 1/3rd octave band-reject filter at the input frequency


FFT Detector Readings		
THD (Channel A)	0.23315 %	< 200 % > 0 %
THD (Channel B)	0.22706 %	< 200 % > 0 %
FFTD 1 Settings: Self relative, 22 Hz - 22 kHz, unweighted with band-pass notch filters from the 2nd to 10th harmonics		
2nd Harmonic Distortion (Channel A)	0.23299 %	< 200 % > 0 %
2nd Harmonic Distortion (Channel B)	0.22692 %	< 200 % > 0 %
FFTD 2 Settings: Self relative, 22 Hz - 22 kHz, unweighted with band-pass notch filter at the 2nd harmonic		
3rd Harmonic Distortion (Channel A)	0.00843 %	< 200 % > 0 %
3rd Harmonic Distortion (Channel B)	0.00798 %	< 200 % > 0 %
FFTD 3 Settings: Self relative, 22 Hz - 22 kHz, unweighted with band-pass notch filter at the 3rd harmonic		
4th Harmonic Distortion (Channel A)	0.00077 %	Not limit checked.
4th Harmonic Distortion (Channel B)	0.00067 %	Not limit checked.
FFTD 4 Settings: Self relative, 22 Hz - 22 kHz, unweighted with band-pass notch filter at the 4th harmonic		
5th Harmonic Distortion (Channel A)	0.00018 %	Not limit checked.
5th Harmonic Distortion (Channel B)	0.00016 %	Not limit checked.
FFTD 5 Settings: Self relative, 22 Hz - 22 kHz, unweighted with band-pass notch filter at the 5th harmonic		
4+HD + N (Channel A)	0.00126 %	< 0.05 % > 0 %
4+HD + N (Channel B)	0.00135 %	< 0.05 % > 0 %
FFTD 6 Settings: Self relative, 22 Hz - 22 kHz, unweighted with band-reject notch filters, fundamental to the 3rd harmonic		
Hum (Channel A)	0.00014 %	< 0.017783 % > 0 %
Hum (Channel B)	0.00055 %	< 0.017783 % > 0 %
FFTD 7 Settings: Self relative, 22 Hz - 22 kHz, unweighted with window notch (14 bins) band-pass filter at 60 Hz		
Noise (residual) (Channel A)	0.00096 %	< 0.017783 % > 0 %
Noise (residual) (Channel B)	0.00116 %	< 0.017783 % > 0 %
FFTD 8 Settings: Self relative, 22 Hz - 22 kHz, unweighted with band-reject notch filters, fundamental to the 10th harmonic		

[Back to top](#)


A05 THD+N vs Freq: PASSED

Measured at 11/20/2020 12:10:08 PM

Generator Settings	
Channel A:	sine, 0 dBu at 1000 Hz
Channel B:	sine, 0 dBu at 1000 Hz



THD+N vs Frequency




[Back to top](#)

## A06 THD+N vs Ampl: PASSED


Measured at 11/20/2020 12:10:15 PM

Generator Settings	
Channel A:	sine, 0 dBu at 1000 Hz
Channel B:	sine, 0 dBu at 1000 Hz

THD+N vs Amplitude



# THD+N vs Amplitude



[Back to top](#)

## A07 Noise, SNR: PASSED

Measured at 11/20/2020 12:10:24 PM

Generator Settings		
Channel A:	sine, -60 dBFS at 1000 Hz	
Channel B:	sine, -60 dBFS at 1000 Hz	
FFT Detector Readings		
Noise (unweighted) (Channel A)	-112.152 dBr	< 200 dBr > -200 dBr
Noise (unweighted) (Channel B)	-111.518 dBr	< 200 dBr > -200 dBr
FFT 1 Settings: 22 Hz - 22 kHz, unweighted with window notch (14 bins) band-reject filter at the generator frequency		
SNR (Channel A)	-112.265 dBr	< 200 dBr > -200 dBr
SNR (Channel B)	-111.682 dBr	< 200 dBr > -200 dBr
FFT 2 Settings: 22 Hz - 22 kHz, unweighted with 1/3rd octave band-reject filter at the generator frequency		

[Back to top](#)

## A08 Crosstalk A to B: PASSED

Measured at 11/20/2020 12:10:26 PM

Generator Settings		
Channel A:	sine, 0 dBu at 1000 Hz	
Channel B:	sine, 0 dBu at 1000 Hz	
CTA Readings		
Cross-talk (Channel B RMS)	-81.892 dB	< -45 dB
Settings: Channel relative, 22 Hz - 22 kHz, unweighted RMS with 1/24th octave band-pass filter at the opposite channel generator frequency		

[Back to top](#)

## A09 Crosstalk B to A: PASSED

Measured at 11/20/2020 12:10:29 PM


Generator Settings		
Channel A:	sine, 0 dBu at 1000 Hz	
Channel B:	sine, 0 dBu at 1000 Hz	
CTA Readings		
Cross-talk (Channel A RMS)	-77.433 dB	< -45 dB
Settings: Channel relative, 22 Hz - 22 kHz, unweighted RMS with 1/24th octave band-pass filter at the opposite channel generator frequency		

[Back to top](#)

A10 Crosstalk A to B vs Freq: PASSED

Measured at 11/20/2020 12:10:31 PM

Generator Settings	
Channel A:	sine, 0 dBu at 1000 Hz
Channel B:	sine, 0 dBu at 1000 Hz




[Back to top](#)

A11 Crosstalk B to A vs Freq: PASSED

Measured at 11/20/2020 12:10:38 PM

Generator Settings	
Channel A:	sine, 0 dBu at 1000 Hz
Channel B:	sine, 0 dBu at 1000 Hz





[Back to top](#)

A12 FFT 1000 Hz THD+N: PASSED

Generator Settings	
Channel A:	sine, 0 dBu at 1000 Hz
Channel B:	sine, 0 dBu at 1000 Hz

Signal Analyzer Readings		
RMS amplitude (Selected : Ch A)	0.063 dBu	Not limit checked.
RMS amplitude (Non-selected : Ch A)	-0.072 dBu	Not limit checked.

CTA Readings		
THD+N - relative (Selected : Ch ARMS)	0.21625 %	< 5 % > 0 %
THD+N - relative (Non-selected : Ch ARMS)	0.21057 %	< 5 % > 0 %
Settings: Self relative, 22 Hz - 22 kHz, unweighted RMS with 1/3rd octave band-reject filter at the input frequency		





[Back to top](#)

A13 FFT 50+7000Hz: PASSED



Generator Settings	
Channel A:	Twin-tone, 0 dBu at 50 Hz and 1 amplitude ratio at 7000Hz
Channel B:	Twin-tone, 0 dBu at 50 Hz and 1 amplitude ratio at 7000Hz

Signal Analyzer Readings		
RMS amplitude (Channel A)	3.066 dBu	Not limit checked.
RMS amplitude (Channel B)	2.923 dBu	Not limit checked.



FFT Detector Readings		
IMD SMPTE-DIN (Channel A)	0.48123 %	< 7 % > 0 %
IMD SMPTE-DIN (Channel B)	0.46727 %	< 7 % > 0 %
FFTD 1 Settings: Self relative, 22 Hz - 22 kHz, unweighted with intermodulation notch band reject		



[Back to top](#)

A14 FFT 600+1700 Hz: PASSED

Measured at 11/20/2020 12:11:31 PM

Generator Settings		
Channel A:	Twin-tone, 0 dBu at 600 Hz and 1 amplitude ratio at 1700Hz	
Channel B:	Twin-tone, 0 dBu at 600 Hz and 1 amplitude ratio at 1700Hz	

Signal Analyzer Readings		
RMS amplitude (Channel A)	3.052 dBu	Not limit checked.
RMS amplitude (Channel B)	2.930 dBu	Not limit checked.



FFT Detector Readings		
IMD SMPTE-DIN (Channel A)	0.50646 %	< 7 % > 0 %
IMD SMPTE-DIN (Channel B)	0.49172 %	< 7 % > 0 %
FFTD 1 Settings: Self relative, 22 Hz - 22 kHz, unweighted with intermodulation notch band reject		

[Back to top](#)



**A15 FFT 19+20 KHz: PASSED**

Measured at 11/20/2020 12:11:53 PM

Generator Settings		
Channel A:	Twin-tone, -16 dBu at 19000 Hz and 1 amplitude ratio at 1000 Hz offset	
Channel B:	Twin-tone, -16 dBu at 19000 Hz and 1 amplitude ratio at 1000 Hz offset	

Signal Analyzer Readings		
RMS amplitude (Channel A)	-12.988 dBu	Not limit checked.
RMS amplitude (Channel B)	-13.135 dBu	Not limit checked.

CTA Readings		
IMD CCIF (Channel A RMS)	0.05237 %	< 1 %
IMD CCIF (Channel B RMS)	0.05053 %	< 1 %
Settings: Self relative, 22 Hz - 22 kHz, unweighted RMS with 1/24th octave band-pass filter at the intermodulation difference frequency		





FFT Detector Readings		
IMD CCIF (Channel A)	0.05194 %	< 1 %
IMD CCIF (Channel B)	0.05045 %	< 1 %
FFT 1 Settings: Self relative, 22 Hz - 22 kHz, unweighted with window notch (14 bins) band-pass filter at the intermodulation difference frequency		

A16 FFT residual noise: PASSED

Measured at 11/20/2020 12:12:17 PM

Generator Settings		
Channel A:		Off
Channel B:		Off

Signal Analyzer Readings		
RMS amplitude (Channel A)	-93.774 dBu	Not limit checked.
RMS amplitude (Channel B)	-93.155 dBu	Not limit checked.



FFT Detector Readings		
Noise (residual) (Channel A)	-100.919 dBu	< -80 dBu > -140 dBu
Noise (residual) (Channel B)	-99.743 dBu	< -80 dBu > -140 dBu
FFTD 1 Settings: 22 Hz - 22 KHz, unweighted with band-reject notch filters, fundamental to the 10th harmonic		